

**SPARE BULB SPECIFICATIONS**

ProductLine	ProductCode	Voltage	Amps / Watts	Bulb	
				Diameter	Length
<b>XD Classic Fairy Light Spare Bulbs</b>	SB100CGC	2.5v	0.1A	6mm	32mm
	SB100CWC	2.5v	0.1A	6mm	32mm
	SB100MCGC	2.5v	0.1A	6mm	32mm
	SB100MCWC	2.5v	0.1A	6mm	32mm
	SB20CGC	12v	0.08A	6mm	32mm
	SB20CWC	12v	0.08A	6mm	32mm
	SB20MCGC	12v	0.08A	6mm	32mm
	SB20MCWC	12v	0.08A	6mm	32mm
	SB50CGC	5v	0.1A	6mm	32mm
	SB50CWC	5v	0.1A	6mm	32mm
	SB50MCGC	5v	0.1A	6mm	32mm
	SB50MCWC	5v	0.1A	6mm	32mm
<b>Traditional LED Spare Bulbs</b>	SBLEDCGC	3v	0.02A	6mm	22mm
	SBLEDMCGC	2v/3v	0.02A	6mm	22mm
<b>B1 Spare Bulbs</b>	0148C	2.4v	0.29w	5.5mm	23mm
	0148M	2.4v	0.29w	5.5mm	23mm
<b>Candle Lights Spare Bulbs</b>	SBCAN	6v	0.1A	5mm	28mm
<b>G1 Spare Bulbs</b>	0344C	6v	0.75w (fuse 0.7w)	5.5mm	28mm
	0344F	6v	0.75w (fuse 0.7w)	5.5mm	28mm
	0344M	6v	0.75w (fuse 0.7w)	5.5mm	28mm
<b>W1 Spare Bulbs</b>	0340C	12v	1.1w	5.5mm	28mm
	0340F	12v	1.1w	5.5mm	28mm
	0340M	12v	1.1w	5.5mm	28mm
<b>Garden Light Spare Bulbs (Starlights)</b>	SBFLOC	12v	3w	21mm	36mm
	SBFLOMC	12v	3w	21mm	36mm
<b>Noma R4 Spare Bulbs</b>	202C	12v	4w (fuse 3.75w)	25mm	25mm
<b>Noma V1 Spare Bulbs</b>	V1 Clear Bulbs	3.6v	0.47w	17mm	48mm
<b>Noma C1 Spare Bulbs</b>	0188	34v	3w		
<b>Spare Bulbs - Clara Clear</b>	24001	24v	1.2w	5mm	7mm
<b>B22 Bulbs</b>	B22	240v	15w	4.5cm	4.5cm